

Specification

Video input	
3G	SMPTE 424M & 425M-AB (2.97 & 2.967Gb/s) 1080p50/59.94/60
HD	SMPTE 292M (1.485 & 1.435Gb/s) 1080i 60/59.94/50 1080p psf 30/29.97/25/24/23.98 720p 60/59.94/50/30/29.97/25/24/23.98
SD	SMPTE 259M-C (270Mb/s) 625i 50 525i 59.94
Number	1
Connector	75Ω BNC
Return loss	>15dB to 1.485GHz >10dB 1.5 to 2.97GHz
Cable equalisation	3G 140m, HD 230m, SD 250m (Belden 1694A)
Video outputs	
Standards	As input
Format	As input
Number	2
Connectors	75Ω BNCs
Jitter	<0.20µi peak-to-peak
Return loss	>15dB to 1.485GHz >10dB 1.5 to 2.97GHz
Embedding	
Standards	SMPTE 299M & 272M-C
Audio inputs	
Inputs	Balanced AES
Number	4
Connector	Female 15pin sub-D (optional XLR breakout cable)
Type	Transformer coupled
Sample rate	32-96kHz
Sample rate conversion	AES converted to 48kHz synchronous with video (selected by dipswitch)
Standard	AES3
Impedance	110Ω
Input level	3.5v p-p +5%
Breakout cable (optional)	4 female XLRs


Electrical	
Voltage	6-12VDC
Power	<3W
Connector	Locking 2.5mm jack (centre +ve)
Safety	EN60950
Control	
Setup	6 way dipswitch
LEDs	Power, input presence & group status
Other	
Size (mm)	63.5 x 84 x 30 plus connectors
Weight	175g
Temperature	5°C to 40°C
Humidity	80% max (non condensing)

Options	
5CA15SD-X05	Audio cable HDD15 to 4F XLRs
4006	Desktop power supply with IEC inlet
NADITBNC-F	Female XLR to BNC adaptor for unbalanced AES input
4010	1U rack mounting frame for up to 5 units including PSU
4020	2U rack mounting frame for up to 14 units & single or dual PSUs
4021	Power supply for 4020 2U frame

DTL MiniBlox™



User Guide




4261D 3G-HD-SD quad AES audio embedder

Inserts four balanced AES digital audio streams into any two groups within an SDI signal

DTL Broadcast Ltd, Johnson's Estate, Silverdale Road, Hayes, Middlesex, UB3 3BA, UK
 Phone: +44 (0) 20 8813 5200 Fax: +44 (0) 20 8813 5022
 Internet: www.dtl-broadcast.com support@dtl-broadcast.com

www.miniblox.com



EU declaration of conformity

We certify that this apparatus conforms to the requirements of the EMC and Low Voltage Directives. Emissions EN55103-1, susceptibility EN55103-2 and safety EN60950-1 2002.

10 February 2009



Warranty

DTL Broadcast Ltd warrants this unit against defects in materials and workmanship for a period of one year from the date of shipment. At its option, the company will repair or replace products that prove to be defective during the warranty period, provided they are returned to the company with advance notification and with freight prepaid. Repairs may only be conducted by an authorised representative of the company. As a result any unauthorised repair or attempted repair will automatically void the warranty.

When a distributor supplies the company's products, that distributor should be approached initially if there are any warranty problems.


The company makes no other warranties, express or implied, as to the merchantability, fitness for a particular purpose, or otherwise. The company's liability for any cause, including breach of contract, breach of warranty, or negligence, with respect to products sold by it, is limited to repair or replacement by the company, at its sole discretion. This remedy is exclusive. In no event shall the company be liable for any incidental or consequential damages, including loss of profits.

Audio inputs

When used with the optional XLR breakout cable inputs are as shown below..

XLR	Input
IN A1	Second group selected - Pair 1
IN A2	Second group selected - Pair 2
IN A3	First group selected - Pair 1
IN A4	First group selected - Pair 2

The pin out of the 15 way sub-D connector is as shown below:



15 way sub-D connector viewed looking in to pins of plug

Pin	Input	Signal
1	Second group selected - Pair 2	+
2	Second group selected - Pair 1	Screen
3	First group selected - Pair 2	+
4	First group selected - Pair 1	Screen
5	Not used	NA
6	Second group selected - Pair 2	-
7	Second group selected - Pair 1	+
8	First group selected - Pair 2	-
9	First group selected - Pair 1	+
10	Not used	NA
11	Second group selected - Pair 2	Screen
12	Second group selected - Pair 1	-
13	First group selected - Pair 2	Screen
14	First group selected - Pair 1	-
15	Not used	NA

Version 1.1 update on 7/02/2011

DTL MiniBlox™ - solutions in a box

General description

The 4261D 3G-HD-SD quad AES audio embedder inserts four balanced AES audio streams (8 audio channels) into the ancillary data space of an SDI signal. Audio can be inserted into any two embedded audio groups. AES inputs can be sample rate converted to a 48kHz rate synchronised to the video. Conversion may be bypassed for compatibility with Dolby® streams. Two units can be cascaded to enable embedding into all four available groups (16 audio channels).


The unit automatically detects whether the SDI input is 3G, HD or 270Mb/s SD SDI. There is automatic input cable equalisation and two re-clocked SDI outputs are provided.

The unit requires an external power supply or a rack mounting frame. A 1RU frame is available which takes up to 5 units and a 2U one that takes up to 14. XLR audio breakout cables and external power supplies are also available.

Key features

- Automatic 3G, HD, or SD SDI standard detection
- Inserts four balanced AES audio streams into any two groups
- Internal sample rate converters for 48kHz AES synchronous with video input
- LEDs show group status and input signal presence
- Automatic input cable equalisation
- 2 re-clocked SDI outputs
- Compact and rugged design
- Optional XLR breakout cable
- Optional external power supply
- Optional rack mounting frames with central power supplies

Functional block diagram



Installation and operation

The unit is simple to use and install.

- Set the dipswitches by referring to the table and description below or the table on the rear of the unit.
- Connect breakout cable (when this option has been ordered).
- Connect a valid SDI input and AES inputs. See the audio input section on the page 6 for connecting to the AES breakout cable or to a 15-pin male sub-D connector (not supplied).
- AES inputs may be synchronous or asynchronous, and of any sample rate up to 96kHz. Alternatively if the sample rate converters are bypassed they must be 48kHz and synchronous to the video input.
- Connect SDI outputs (if required).
- Apply power to the unit either via the locking power connector from the external power supply or 1U rack frame, or by sliding into the 2U rack mounting frame with central power supplies.
- On power-up the unit will perform a short (3 second) self test. The group LEDs will flash while this is in progress.
- The signal LED will be green when there is power and a valid SDI signal present or red when there is power but no SDI signal.
- Two group LEDs will light corresponding to the groups selected by the dipswitches (default on delivery groups 1&2). The LED will be green if the unit is receiving a valid video signal and successfully embedding audio from that group. The LED will otherwise be red. Orange LEDs indicate which groups are already present in the SDI stream.
- The switch settings can be altered whilst the unit is powered and the changes are implemented immediately. Switch 1 is used to toggle through all possible pairs of groups into which to insert audio.
- The mounting bracket supplied can be used to install the unit. The bracket should first be fixed vertically to any surface. The MiniBlox can then be lowered onto the dovetail part of the bracket with the front endplate uppermost to retain it.

Switch settings

Switch	OFF	ON
1	Toggle audio group A	
2	Toggle audio group B	
3	Cascade	Overwrite
4	24-bit SD	20-bit SD
5	DS1	DS2
6	SRC on	SRC bypass

Switches 1& 2 are used to select the two groups into which the audio samples are inserted. Toggling switch 1 or 2 will cycle through all possible groups with

the group selected shown on the LEDs. The group settings are stored in EEPROM and are therefore retained even after the unit has been powered down.

Switch 3 determines whether existing audio packets are deleted from the video signal. When the switch is off, new audio packets are appended without deletion of existing packets allowing two units to be connected in cascade.

Switch 4 controls the bit depth of the embedded audio for SD SDI only (audio depth is always 24 bit in 3G & HD). When the switch is off, extended audio packets are multiplexed into the video signal (24 bit audio). When the switch is on, extended audio packets are not included (20 bit audio).

Switch 5 selects between embedding on data stream one or two when embedding to a 3G Level B signal.

Switch 6 is used to bypass the sample rate conversion.